

## Circular Saw LXT DHS680RFJ



### Product Description

18V LXT • 5 000 min<sup>-1</sup> • 165 mm

#### Efficient and compact brushless professional saw

An efficient brushless and cordless circular saw for wood. Accepts blades with 165 mm diameter that achieve a max. cutting depth of 57 mm. Ventilation air is guided through the front to keep the cut line clear and an LED light offers added illumination. Compatible with a guide rule. Includes 2 x 3,0 Ah batteries and a charger in a Makpac case.

### Product Features

- ⊙ LED light illuminates the work site
- ⊙ Battery protection system automatically shuts off power when the battery level is low
- ⊙ The safety switch prevents accidental start-up of the tool
- ⊙ The rubber coating on the handle ensures a firm working grip
- ⊙ Removable dust extraction connection

### Barcode

88381684385

### Product Specifications

<b>Bore Size (Arbor Diameter)</b>	20 mm
<b>Max. Cutting Depth at 45°</b>	41 mm
<b>Capacity 45° (Miter R/L 45°, Bevel 0°)</b>	41 mm
<b>Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)</b>	Li-ion
<b>Tool weight with battery (EPTA)</b>	3,0 - 3,3 kg
<b>Brushless Motor</b>	YES
<b>Battery Voltage</b>	18 V
<b>Max. Cutting Depth at 50°</b>	37 mm
<b>Max. Bevel Range (Left)</b>	0 / 50 °
<b>Sound Pressure Level</b>	94 dB(A)
<b>Product Dimensions (L x W x H):</b>	350 x 170 x 238 mm
<b>Vibration Level (3 axes)</b>	≤ 2,5 m/s <sup>2</sup>
<b>Sound Power Level (L<sub>WA</sub>)</b>	105 dB(A)
<b>Voltage LXT</b>	1
<b>System</b>	LXT 18V/36V
<b>Product net weight (new)</b>	2,7 kg
<b>Vibration Uncertainty (K Factor)</b>	1,5 m/s <sup>2</sup>
<b>Noise Uncertainty (K Factor)</b>	3 dB(A)
<b>Vacuum cleaner connection Ø in / out</b>	35/40 mm
<b>Tool Category</b>	Sawing
<b>Max. Cutting Depth at 90°</b>	57 mm

<b>Blade Diameter</b>	165 mm
<b>Max Output Power</b>	680 W
<b>No load speed</b>	5000 min <sup>-1</sup>

### Standard Equipment

- ⊙ 1pc DC18RC Fast Charger
- ⊙ 2pcs BL1830B (3.0Ah) 18V LXT Battery
- ⊙ Makpac Case

### More info

<https://makita.ae/product/circular-saw-lxt-dhs680rfj/>