

## Blower LXT DUB362Z



### Product Description

36V (18Vx2) LXT • 54 m/s • 13,4 m<sup>3</sup>/min

#### Efficient brushless blower for demanding use

A versatile and extremely efficient blower for construction and gardening. Equipped with a brushless motor and two 18V LXT batteries that achieve a voltage of 18V+18V. The blow tube length can be adjusted up to 100 mm, speed control from a switch. Tool only, battery and charger not included.

### Product Features

- Battery protection system automatically shuts off power when the battery level is low

### Barcode

88381693110

### Product Specifications

<b>Continuous use 18V / 6.0 Ah battery</b>	13,5 - 89 min
<b>Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)</b>	Li-ion
<b>Tool weight with battery (EPTA)</b>	3,5 - 4,2 kg
<b>Continuous use 18V / 4.0 Ah battery</b>	61 / 34 / 23 / 17 / 13 / 9
<b>Battery Voltage</b>	2 x 18 V
<b>Brushless Motor</b>	YES
<b>Sound Pressure Level</b>	79,1 dB(A)
<b>Vibration Uncertainty (K Factor)</b>	1,5 m/s <sup>2</sup>
<b>Product Dimensions (L x W x H):</b>	930 x 205 x 295 mm
<b>Vibration Level (3 axes)</b>	≤ 2,5 m/s <sup>2</sup>
<b>Sound Power Level (L<sub>WA</sub>)</b>	93,5 dB(A)
<b>Max. Air Velocity</b>	54 m/s
<b>Voltage LXT</b>	1
<b>System</b>	LXT 18V/36V
<b>Product net weight (new)</b>	2,8 kg
<b>Noise Uncertainty (K Factor)</b>	2,3 dB(A)
<b>Tool Category</b>	Dust Management
<b>Air volume</b>	13,4 m <sup>3</sup> /min
<b>Blowing force</b>	3,7 / 5,6 / 7,8 / 9,8 / 11,6 / 14,4 N
<b>No load speed</b>	11400 - 21500 min <sup>-1</sup>
<b>Continuous use 18V / 3.0 Ah battery</b>	44 / 25 / 16 / 12 / 9 / 6
<b>Continuous use 18V / 5.0 Ah battery</b>	75 / 42 / 28 / 20 / 16 / 11

## Standard Equipment

◎ Sold without Battery or Charger

More info

<https://makita.ae/product/blower-lxt-dub362z/>