

# Blower LXT

## DUB362Z



### Product Description

36V (18Vx2) LXT • 54 m/s • 13,4 m<sup>3</sup>/min

#### Efficient brushless blower for demanding use

A versatile and extremely efficient blower for construction and gardening. Equipped with a brushless motor and two 18V LXT batteries that achieve a voltage of 18V+18V. The blow tube length can be adjusted up to 100 mm, speed control from a switch. Tool only, battery and charger not included.

### Product Features

- ⊙ Battery protection system automatically shuts off power when the battery level is low

### Barcode

88381693110

### Product Specifications

Continuous use 18V / 6.0 Ah battery	13,5 - 89 min
Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)	Li-ion
Tool weight with battery (EPTA)	3,5 - 4,2 kg
Continuous use 18V / 4.0 Ah battery	61 / 34 / 23 / 17 / 13 / 9
Battery Voltage	2 x 18 V
Brushless Motor	YES
Sound Pressure Level	79,1 dB(A)
Vibration Uncertainty (K Factor)	1,5 m/s <sup>2</sup>
Product Dimensions (L x W x H):	930 x 205 x 295 mm
Vibration Level (3 axes)	≤ 2,5 m/s <sup>2</sup>
Sound Power Level (L <sub>WA</sub> )	93,5 dB(A)
Max. Air Velocity	54 m/s
Voltage LXT	1
System	LXT 18V/36V
Product net weight (new)	2,8 kg
Noise Uncertainty (K Factor)	2,3 dB(A)
Tool Category	Dust Management
Air volume	13,4 m <sup>3</sup> /min
Blowing force	3,7 / 5,6 / 7,8 / 9,8 / 11,6 / 14,4 N
No load speed	11400 - 21500 min <sup>-1</sup>
Continuous use 18V / 3.0 Ah battery	44 / 25 / 16 / 12 / 9 / 6
Continuous use 18V / 5.0 Ah battery	75 / 42 / 28 / 20 / 16 / 11

---

## Standard Equipment

- ⦿ Sold without Battery or Charger

## More info

<https://makita.ae/product/blower-lxt-dub362z/>