

## Dust Blower LXT DAS180RF



### Product Description

18V LXT • 0 - 150 m/s • 0 - 18,0 kPa • 0 - 1,1 m<sup>3</sup>/min

#### **Cordless Air Duster with a variety of tip nozzles**

Handy air duster for cleaning tools, boreholes, filters etc. Comes with 5 different nozzles. It can also be used to inflate or deflate inflatable toys, inner tubes, play pools and more. Air duster has LED job light with preglow and afterglow functions. Comes with one 3,0 Ah battery and one charger.

### Product Features

- ⊙ Battery protection system automatically shuts off power when the battery level is low
- ⊙ 4 stage air volume; selectable according to your application
- ⊙ Brushless maintenance-free and long-life motor
- ⊙ Battery capacity warning function automatically notifies the user about reduction in battery capacity with the decrease of illuminance

### Barcode

88381780001

### Product Specifications

<b>Max. sealed suction</b>	103 mbar
<b>Continuous use 18V / 6.0 Ah battery</b>	55 / 30 / 20 / 15 min
<b>Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)</b>	Li-ion
<b>Tool weight with battery (EPTA)</b>	1,2 - 1,7 kg
<b>Brushless Motor</b>	YES
<b>Battery Voltage</b>	18 V
<b>Product Dimensions (L x W x H):</b>	173 x 92 x 247 mm
<b>Sound Pressure Level</b>	82 dB(A)
<b>Anti-Restart Function (NVR Switch)</b>	1
<b>Vibration Uncertainty (K Factor)</b>	1,5 m/s <sup>2</sup>
<b>Vibration Level (3 axes)</b>	≤ 2,5 m/s <sup>2</sup>
<b>Max. Air Velocity</b>	0 - 200 m/s
<b>Sound Power Level (L<sub>WA</sub>)</b>	90 dB(A)
<b>Voltage LXT</b>	1
<b>Product net weight (new)</b>	1,0 kg
<b>System</b>	LXT 18V/36V
<b>Noise Uncertainty (K Factor)</b>	3 dB(A)
<b>Tool Category</b>	Dust Management
<b>Blowing force</b>	0 - 1,1 / 1,7 / 2,3 / 2,8 N

**Air volume**

0 - 1,1 m<sup>3</sup>/min

Standard Equipment

- ⦿ 1pc DC18RC Fast Charger
- ⦿ 1pc BL1830B (3.0Ah) 18V LXT Battery

More info

<https://makita.ae/product/dust-blower-lxt-das180rf/>