

## Impact Wrench LXT DTW300Z



### Product Description

18V LXT • 1/2" • 330 Nm • 0 - 3 200 min<sup>-1</sup>

**Extra-compact and efficient brushless impact wrench with three power settings. (C ring)**

Powerful and extra-compact, 144 mm-long, 1/2" drive impact wrench. Small size and light weight make this tool easy to use, while offering a max. fastening torque of 330 Nm. Four power settings. A handy LED light. Tool only, battery and charger not included.

### Product Features

- ⊙ Extremely compact thanks to a brushless motor
- ⊙ Low power consumption thanks to brushless motor
- ⊙ The narrow design of the handle ensures excellent handling
- ⊙ Battery protection system automatically shuts off power when the battery level is low
- ⊙ XPT (Extreme Protection Technology) is engineered for improved dust and water resistance for operation in harsh job site conditions

### Barcode

88381898003

### Product Specifications

<b>Drive Square</b>	0.5 "
<b>Tool weight with battery (EPTA)</b>	1,5 - 1,8 kg
<b>Battery Voltage</b>	18 V
<b>Brushless Motor</b>	YES
<b>Vibration Level (3 axes), Fastening Bolt</b>	12,5 m/s <sup>2</sup>
<b>Sound Pressure Level</b>	97 dB(A)
<b>Vibration Uncertainty (K Factor)</b>	1,5 m/s <sup>2</sup>
<b>Tightening Capacity High Tensile Bolt</b>	M10 - M16

<b>Product Dimensions (L x W x H):</b>	144 x 81 x 246 mm
<b>Sound Power Level (L<sub>WA</sub>)</b>	108 dB(A)
<b>Impacts per Minute (IPM)</b>	0 - 1800 / 2600 / 3400 / 4000 min <sup>-1</sup>
<b>Max Fastening Torque Impact Drill</b>	100 / 160 / 210 / 330 Nm
<b>Voltage LXT</b>	1
<b>System</b>	LXT 18V/36V
<b>Product net weight (new)</b>	1,2 kg
<b>Tightening Capacity Standard Bolt</b>	M10 - M20
<b>Noise Uncertainty (K Factor)</b>	3 dB(A)
<b>Tool Category</b>	Screwing and Drilling
<b>Max Output Power</b>	420 W
<b>No load speed</b>	0 - 1000 / 1800 / 2600 / 3200 min <sup>-1</sup>
<b>Nut-busting torque</b>	580 Nm

#### Standard Equipment

- ⊙ Sold without Battery or Charger

#### More info

<https://makita.ae/product/impact-wrench-lxt-dtw300z/>