

## Job site radio XGT MR001GZ01

### Product Description

40V MAX XGT • 18V LXT

**Compatible with CXT®, LXT®, XGT®, batteries.**

Dual Power Sources: AC or Makita batteries



### Product Specifications

Frequency Range FM	87,5 - 108 MHz
Continuous use 18V / 6.0 Ah battery	31 h
Tool weight with battery (EPTA)	4,5- 5,3 kg
Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)	Li-ion
Speaker Output Power 40Vmax	5 W (x2)
Continuous use 18V / 4.0 Ah battery	20 h
Battery Voltage	12 / 14,4 / 18 / 40 V
Continuous use 18V / 2.0 Ah battery	10 h
CXT Battery	1
Product Dimensions (L x W x H):	280 x 171 x 298 mm
Frequency Range AM	522 - 1 710 kHz
Continuous use 14.4V / 3.0 Ah battery	12 h
Product net weight (new)	4,3 kg
System	XGT 40Vmax/80V max
Continuous use XGT® 40Vmax / 4,0 Ah	30 h
Voltage LXT	1
Voltage XGT	1
Speaker Output Power 12Vmax	1,2 W (x2)
Tool Category	Audio
Speaker Output Power 18V	3,5 W (x2)

<b>International Protection Class (IP)</b>	IP65
<b>Continuous use 18V / 5.0 Ah battery</b>	25,5 h
<b>Continuous use 18V / 3.0 Ah battery</b>	14 h

### Standard Equipment

- ⦿ Sold without Battery or Charger

### More info

<https://makita.ae/product/job-site-radio-xgt-mr001gz01/>