

# Percussion Driver Drill LXT DHP484Z

Makita



## Product Description

18V LXT • 54 Nm • 0 - 2 000 min<sup>-1</sup>

# A powerful, brushless general-use impact drill for screwdriving and drilling

An efficient, brushless drill for professional screwdriving and drilling with or without hammer action, two power settings. Max. torque of 54 / 30 Nm. A versatile tool for fitters, builders and maintenance staff. Integrated LED light. Tool only, battery and charger not included.

### **Product Features**

● LED light illuminates the work site

Battery protection system automatically shuts off power when the battery level is low

Mechanical 2-speed gearing; High speed mode for speedy drilling in light duty applications; Low speed
 mode for heavy duty applications requiring high torque

• Electric brake for maximum productivity and increased operator safety

• Reversing switch is conveniently located

#### Barcode

#### 88381826105

Product Specifications		
Vibration Level (3 axes), Drilling	≤ 2,5 m/s²	
Torque setting	21	
Max. Drilling Diameter in Steel	13 mm	
Max. Drilling Diameter in Wood	38 mm	
Vibration Level (3 axes), Impact Drilling	8,0 m/s²	
Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)	Li-ion	
Tool weight with battery (EPTA)	1,6 - 1,9 kg	
Brushless Motor	YES	
Battery Voltage	18 V	
Sound Pressure Level	88 dB(A)	
Product Dimensions (L x W x H):	182 x 79 x 261 mm	
Max. fastening torque Hard/Soft	54 / 30 Nm	
Impacts per Minute (IPM)	0 - 7500 / 30000 min <sup>-1</sup>	
Sound Power Level (L <sub>wa</sub> )	99 dB(A)	

Voltage LXT	1
System	LXT 18V/36V
Product net weight (new)	1,2 kg
Vibration Uncertainty (K Factor)	1,5 m/s²
Driving Shank	1/2"-20UNF "
Noise Uncertainty (K Factor)	3 dB(A)
Tool Category	Screwing and Drilling
Drill Chuck Capacity	1,5-13 mm
Electronic brake	1
Max. Drilling Diameter in Masonry	13 mm
Max. Drilling Diameter in Concrete	13 mm
No load speed	0 - 500 / 2000 min <sup>-1</sup>

Standard Equipment

 $\circledast$  Sold without Battery or Charger

More info

https://makita.ae/product/percussion-driver-drill-lxt-dhp484z/