

## Radio CXT / LXT

# DMR107Z



### Product Description

7,2V - 18V LXT

#### High-fidelity radio for work and leisure

A radio with high-quality reproduction of sound for worksites or summer cottage. Runs on 7.2 - 18V Li-ion batteries or a mains adapter included in the delivery. AUX connectivity and LCD display. Tool only, battery and charger not included.

### Product Features

- ⦿ Can be operated with all Makita Li-Ion batteries 7.2 - 18 V - also with the new 10.8 V sliding batteries, but not with Makita mt, maktec or G-series batteries
- ⦿ Battery protection system automatically shuts off power when the battery level is low

### Product Specifications

|   |                        |
|---|------------------------|
| <b>Frequency Range FM</b>                         | 87,5 - 108 MHz         |
| <b>Continuous use 18V / 6.0 Ah battery</b>        | 42 h                   |
| <b>Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)</b> | Li-ion                 |
| <b>Tool weight with battery (EPTA)</b>            | 4,2 - 4,6 kg           |
| <b>Continuous use 18V / 4.0 Ah battery</b>        | 28 h                   |
| <b>Battery Voltage</b>                            | 7,2 / 12 / 14,4 / 18 V |
| <b>Continuous use 12Vmax / 1.5 Ah battery</b>     | 9,5 h                  |
| <b>Continuous use 12Vmax / 4.0 Ah battery</b>     | 26 h                   |
| <b>Continuous use 18V / 2.0 Ah battery</b>        | 14 h                   |
| <b>CXT Battery</b>                                | 1                      |
| <b>Power Supply Cord</b>                          | 1,8 m                  |
| <b>Product Dimensions (L x W x H):</b>            | 280 x 163 x 302 mm     |
| <b>Continuous use 14.4V / 3.0 Ah battery</b>      | 20 h                   |
| <b>Frequency Range AM</b>                         | 522 - 1629 kHz         |
| <b>Voltage LXT</b>                                | 1                      |
| <b>System</b>                                     | LXT 18V/36V            |

|   |            |
|---|------------|
| <b>Product net weight (new)</b>               | 4,0 kg     |
| <b>Tool Category</b>                          | Audio      |
| <b>Speaker Output Power 12Vmax</b>            | 1,2 W (x2) |
| <b>Speaker Output Power 18V</b>               | 3,5 W (x2) |
| <b>International Protection Class (IP)</b>    | IP64       |
| <b>Continuous use 18V / 5.0 Ah battery</b>    | 35 h       |
| <b>Continuous use 18V / 3.0 Ah battery</b>    | 21 h       |
| <b>Continuous use 12Vmax / 2.0 Ah battery</b> | 12 h       |

#### Standard Equipment

⦿ Sold without Battery or Charger

#### More info

<https://makita.ae/product/radio-cxt-lxt-dmr107z/>